



## MATERIAL FACT SHEET

### 247605 FR-D740-080SC-EC

#### General Data

Product Hierarchy	IAK23801
	INVERTER
	FR-D740
Ext. Material Group	10 STANDARD ITEM
ABC Indicator	A (Available from Stock)

#### FA-Inverter: Inverter

Series	FR-D700 SERIES
Type	FR-D700 COMPACT INVERTER
Minimum Rated Voltage (V)	380
Min. Permissible Voltage (V)	325
Maximum Rated Voltage (V)	480
Max. Permissible Voltage (V)	528
Current Type	AC
Phases	3
Rated Output Current ND (A)	8
Rated Motor Capacity ND (kW)	3,7
Frequency Range (Hz)	0,2-400
Control Method	MAGNETIC FLUX VECTOR CONTROL
Control Method (2)	SOFT-PWM/HIGH FREQUENCY PWM
Control Method (3)	V/F CONTROL
Motor Type	INDUCTION MOTOR
Brake Chopper ED (%)	30
Integrated EMC Filter	NO
Safe Torque Off (STO)	YES
Regenerative (4Q)	NO
Integrated DC Choke	NO
Display	BUILT-IN
Display Type	4 DIGITS LED
PLC Function	NO
Integrated Digital Inputs	5
Digital Outputs (Transistor)	1
Digital Outputs (Relay)	1
Integrated Analogue Inputs	2
Integrated Analogue Outputs	1
IO Type of Terminal Block	SPRING CLAMP
Expandable	NO
RS-485	1
USB	NO
Ethernet Port	NO
Built-In Network	MODBUS-RTU
Leakage Current (mA)	1
Power Loss ND (W)	180
Standby Power Consumption (W)	10,5-17
Protection Class	IP20

#### Product Dimensions & Weight

Width (mm)	108
Height (mm)	128
Depth (mm)	165,5
Weight (kg)	1,5

#### Logistic Dimensions & Gross Weight

Length (cm)	22,0
-------------	------

Width (cm)	19,0
Height (cm)	20,5
Gross Weight (kg)	1,900
Volume (cdm)	8,569

### Stock Data

Planned Delivery Time (Days)	296
------------------------------	-----

### Life Cycle

Sales Start	05.03.2012
Predecessor	212418 / FR-D740-080-EC

### Export Data

Commodity Code	85044095
Legal Control (Dual Use List)	Not Listed
Country of Origin	China (CN)
Preference Status (Supplier Declaration)	Non EU

### Environmental

Dangerous Goods Class	NO
Dangerous Goods Identifier	NO
RoHS Compliance	COMPLIANT
WEEE	B2B

### Conformity

CE	COMPLIANT
UL/cUL	COMPLIANT
EAC	COMPLIANT
UKCA	COMPLIANT

### Product Packaging

Cardboard (g)	363,8
Other paper (g)	0
Aluminum (g)	0
Steel (g)	0
Styrofoam (g)	0
Other plastic (g)	2,2
Wood (g)	0
Glass (g)	0
Others (g)	0

### Spare parts

Material	Description	Quantity	Unit
164630	FR-F740-00083-00126 FAN	1	PC

### Compatible products

Material	Description / Price List Text / Classification
46413	FR-ABR-H3.7K External High-Duty Brake Resistor; 400V; 3,7kW; 150 Ohm; 10%ED Class 100100407: FA-Inverter: Brake Option
70727	FR-A5 CBL 1 Cable for connecting Inverter and Programming panel; 1m Class 100100405: FA-Inverter: Cable
70728	FR-A5 CBL 2,5 Cable for connecting Inverter and Programming panel; 2,5m Class 100100405: FA-Inverter: Cable
70729	FR-A5 CBL 5 Cable for connecting Inverter and Programming panel; 5m Class 100100405: FA-Inverter: Cable

Material	Description / Price List Text / Classification
<u>87244</u>	FR-BAL-B-4,0K Input Reactor 3ph; 400V; for 4,0kW Class 100100406: FA-Inverter: Choke
<u>88426</u>	SC-FR-PC CONNECTION CABLE PC>INVERTER Programming Cable RS 232>RS485/422; 5m Class 100100405: FA-Inverter: Cable
<u>127947</u>	BU-UFS 22 Brake Unit 400V; Contin. Braking Current 22A; 10sec peak current 34A Class 100100407: FA-Inverter: Brake Option
<u>129629</u>	RUF22 (PACK OF 1) Brake Resistor for BU-UFS22; 2kW; 1x24 Ohm Class 100100407: FA-Inverter: Brake Option
<u>130832</u>	FR-UDA02 DIN-Rail Adaptor for FR-D720S-1,5k; FR-D740-0,4k-3,7k Class 100100403: FA-Inverter: External Option
<u>157514</u>	FR-DU07 Parameter Unit for inverter type FR-A700-NA Class 100100403: FA-Inverter: External Option
<u>157515</u>	FR-ADP Adaptor Module for Operator Panel FR-DU07 Class 100100403: FA-Inverter: External Option
<u>166134</u>	FR-PU07 Programming panel with LCD-Display for all units of FR-700 series Class 100100403: FA-Inverter: External Option
<u>209052</u>	FR-PU07BB-L Programming Panel with Copy Function; batterypowered; all FR-700 units; w/o bat. Class 100100403: FA-Inverter: External Option
<u>209737</u>	FFR-SI-18A-SS1 Sinusfilter for 200/230/400V Inverters; max. 18A; FT=4-16kHz; (W*H*D) 190*230*120mm Class 100100404: FA-Inverter: Filter
<u>209755</u>	FFR-DT-10A-SS1 du/dt Filter for 400V Inverters; max. 10A; FT=2-16kHz; (W*H*D) 100*120*65mm Class 100100404: FA-Inverter: Filter
<u>214795</u>	FR-PA07 Simple Parameter Unit for mounting on enclosure surface; for all FR-E700 Class 100100403: FA-Inverter: External Option
<u>238346</u>	FFR-HEL-H3.7K-E DC Link choke for 400V Inverter; 3,7kW; 8,81mH; 7,1A Class 100100406: FA-Inverter: Choke
<u>247644</u>	BH-D6 3P 20A TYPE C N MCB 3-poles, Rated current 20A, Operating characteristic C Class 100100801: FA-MCB: Miniature Circuit Breaker
<u>254746</u>	NF63-SV 3P 20A Circuit breaker 3pole. In = 20A; Icu = Ics = 7,5kA at AC 440V Class 100100901: FA-MCCB: Moulded-Case Circuit Breaker
<u>275503</u>	FR Configurator-M+FR-Configurator2 FR-Configurator for 700 series; multi I + FR-Configurator2 for 800 series Class 100101203: FA-Software: Software Inverter
<u>279143</u>	S-T10 AC200V 1A Magnetic contactor. 4kW; 1NO; Us = AC 200V, 50Hz Class 100101001: FA-MC: Magnetic Contactor
<u>287431</u>	SD-T12 DC24V 1A1B Magnetic contactor. 5,5kW; 1NO + 1NC; Us = DC 24V Class 100101001: FA-MC: Magnetic Contactor
<u>312333</u>	FFR-CSH-080-16A-SF1 Radio Noise Filter for FR-D740-050/080-EC; FR-CS84-050-080; C1 20m; C2 100m Class 100100404: FA-Inverter: Filter
<u>312345</u>	FFR-CSH-080-16A-SF2-LL Radio Noise Filter for FR-D740-050/080; C1 10m, C2 30m Class 100100404: FA-Inverter: Filter